

Wireless Doorbell/Intercom System

Wireless Door Intercom System (E1000)



Features

The ERA E1000 Wireless Door Intercom system allows you to conveniently answer your doorbell and speak with the visitor within the comfort of your home. With no wiring required between the Outdoor Station (intercom/doorbell) and the Indoor Portable Handset, this intercom system is quick and easy to install. Suitable for both residential and commercial use and has an operating range of up to 200 metres from the handset to intercom.

- Prevents doorstop intrusion
- 'Two-Way' conversation
- Convenient portable handset for use anywhere in the home
- Flashing visual ringer
- Choice of five ring tones
- Adjustable volume
- Long operating range of up to 200 metres from the Outdoor Station
- Power indicator and in-use indicator
- Charging dock with charge indicator
- Outdoor Station is weatherproof IP56
- Single button door release with door unlock module (sold separately and requires compatible electronic door lock)
- All batteries and fixings included
- Optional accessories include Outdoor Station Rain Cover, Outdoor Station Power Supply, Unlock Module

Key Features

• Two-way talk, speak with the visitor at your door conveniently and safely

HONTE STATART

- Audible and visual alerts, handset sounds and flashes when doorbell is in operation
- Long operating range of up to 200m
- Five ring tones and five volume levels available

Ordering Details	
Product	Part No.
Wireless Door Intercom Additional Accessories	E1000
Outdoor Station Rain Cover Outdoor Station Power Supply Unlock Module	CLOSRC CLOPSU CL3660UM

Technical Information

ltem	Parameter
item	raiametei
Model No	E1000
Frequency	1.88 - 1.90GHz
Number of Channels	120, Duplex Channels
Time Accuracy	0 ± 2ppm
Frequency Stability	< ± 50KHz
Modulation	GFSK
Standby Time	7hrs
Battery Charging Time	15hrs
Temperature Range	0° - 40°C
Relative Humidity	0% - 90%
Dimensions - Charging Dock (mm)	132 x 132 x 68.5
Dimensions - Intercom Handset (mm)	133 x 46 x 19.5
Dimensions - Outdoor Station (mm)	177 x 60 x 34
Charging Dock	DC 7.5V / 300mA (adapter included)
Intercom Handset	2 Rechargeable AAA Ni-MH 1.2V / 600mAh (included)
Outdoor Station	2 x 1.5V LR14 or 12V DC Power Supply
Operating range	Door Intercom to Outdoor station up to 200 metres
Current Consumption - Handset	Max 1.33mA (Standby) / 200mA (Conversation)
Current Consumption -	Max 0.8mA (Standby) / 200mA
Outdoor Station	(Conversation)
IP Rating	Doorbell/Intercom unit suitable for outdoor use - IP56
Colour	Black and Silver

Packaging

Kit Content

Outdoor Station (doorbell/intercom) x 1, Portable Handset x 1, Handset Charging Dock x 1, Handset Power Adaptor x 1, Handset Belt Clip x 1, Installation and Operating Manual, all Fixings and Batteries

