



01948 667 600



info@securasound.co.uk



The Hollies, Chester rd,
Whitchurch, SY13 1LZ

Engineering data sheet



K40965

Wi-Fi Video doorbell kit



- External Video door Bell
- Wired connection from Door Bell to PSU
- Call forwarding to Vimar View Door App via the dwellings WiFi
- 12V DC Lock output (if required)
- Secondary clean contact output (if required)
- Motion and person detection
- Video and picture recording to SD Card
- Compatible with Amazon Alexa voice assistant
- No subscription fees

General information

The Vimar Wi-Fi video doorbell allows you to check and identify who is ringing your doorbell. The doorbell unit incorporates a 12V DC lock output (if required) and a secondary clean contact for gate release (if required)

The video doorbell is configured using the Vimar view door app and a local Bluetooth connection to the doorbell from a smartphone.

The video doorbell is compatible with Amazon Alexa voice assistants.

The video doorbell is supplied with an 8Gb micro SD card (this is expandable up to 128Gb) for storage of video and photographs from the camera unit.

An additional wireless ringtone can be added for call repetition.

The Vimar View Door app is subscription free but requires a MyVimar account to be configured for installer and user(s)

Specifications

System Vimar Wi-Fi Door Bell

Power Supply 230V AC to 24V DC

Doorbell Protection IP54

Video/Audio 4 Mpx resolution, 160 degree wide angle lens, full duplex audio

Lock & Auxiliary 12V DC Lock output with auxiliary clean contacts

Detection Motion detection with programmable zones and person detection

Recording 8 Gb SD card supplied, pre-roll function allowing recording of events 5 seconds before motion detection.

Tamper Tamper detection with notification

Configuration Via app on smartphone, MyVimar account required for installer and user(s)